

Таблица моделей с метрической резьбой (М)



Тип кабельного ввода	Диаметр вводимого кабеля мм	Длина резьбы мм	Диаметр монтажного отверстия мм	Ключ
M8x1.25	2 - 5	5	8	-
M10x1.5	3 - 6.5	7	10	14
M12x1.5	3 - 6.5	7	12	14
M14x1.5	4 - 8	7	14	17
M16x1.5	4 - 8	8	16	18
M18x1.5	5 - 10	8	18	20
M20x1.5	6 - 12	8	20	22
M22x1.5	10 - 14	8	22	24
M24x1.5	10 - 14	9	24	24/27
M25x1.5	10 - 14	9	25	24/27
	12 - 16			27
	13 - 18			30/27
M27x1.5	13 - 18	9	27	30
M28x1.5	13 - 18	9	28	30
M30x1.5	13 - 18	9	30	30/32
M32x1.5	15 - 22	10	32	30/32
M33x1.5	15 - 22	10	33	-
M36x1.5	18 - 25	10	36	-
M37x1.5	18 - 25	10	37	-
M40x1.5	18 - 25	11	40	-
	22 - 30			
M42x1.5	22 - 30	11	42	-
M47x1.5	25 - 33	11	47	-
M48x1.5	25 - 33	11	48	-
M50x1.5	32 - 38	12	50	-
M54x1.5	32 - 38	12	54	-
M60x1.5	37 - 44	13	60	-
M63x1.5	37 - 44	13	63	-
M64x2	37 - 44	13	64	-
M72x2	42 - 52	15	72	-
M75x2	42 - 52	15	75	-
M80x2	55 - 62	15	80	-
M88x2	65 - 70	15	88	-
M100x2	78 - 84	15	100	110